

MAG-Z112/ MAG-Z114

2/ 4-Port HDMI KVM Switch w/ Hotkey Control

► Specifications

		MAG-Z112	MAG-Z114
Console Port		1	1
Computer Port		2	4
Front Panel Push Button		1	5
Automatic Scan Interval		3, 8, 15, 30 Seconds	
Cable Length (Max)		3M (10ft) for USB	
Computer ON-LINE LED		2	4
Computer Selected LED		2	4
Hot Plug-and-Play		Yes	Yes
Console Interface	USB Port	KB+MS	
	KB	USB-A	USB-A
	MS	USB-A	USB-A
	Monitor	HDMI	HDMI
Computer Interface	KB	USB-B	USB-B
	MS		
	Monitor	HDMI	HDMI
Hotkey		Yes	Yes
OSD		No	No
Resolution		1920 x 1080	1920 x 1080
DDC2B		Yes	Yes
H x W x D (mm)		40 x 126 x 65	44 x 220 x 130

► Features

- Support USB console
- Supports hot plug and un-plug detection and link status-failure detection
- Supports high video resolution up to Full HD (1920 x 1080)
- Front panel push buttons for easy computer selection
- Selectable Scan Time interval
- Activates Auto Scan by front buttons pressing (available for 4-Port Type)
- Buzzer sound for computer switching confirmation
- Hotkey functions allow easily computer access
- Supports keyboard and mouse plug-n-play
- Screw-free design ,streamlined form factor for new all digital desktop monitors
- Complete interoperability
- No drivers needed; No software required
- Support Windows and Mac host systems
- Supports Windows/ Mac Multimedia function keys

► Connection Pattern

